

## TWN4 Slim

# Multi-frequency RFID reader (LF/HF) with NFC and BLE support



TWN4 Slim (exemplary illustrations)

Even smaller than an ID-1 card – The RFID readers of the TWN4 Slim family are ELATEC most compact and flat readers. All devices are available with an NXP or LEGIC frontend and support NFC and Bluetooth Low Energy (BLE) technologies, which makes the readers an ideal solution for mobile data communication and authentication applications. In addition, they are equipped with a flexible micro USB cable and, optionally, with mounting holes that enable a quick and easy installation into any industrial application, especially MFP printers. The readers are available as part of a kit with several accessories (e.g. cables, mounting frame or snap-in covers for printers) or as a standalone unit working with a PC or any other device equipped with a USB interface.

Key features of the TWN4 Slim reader include an extremely compact form factor that enables a smooth integration into almost any host system, an optimized design for industrial and secure printing applications, and a powerful SDK for writing apps that are executed directly on the reader. Additionally, the reader can read more than 60 RFID technologies from low (LF) and high frequency (HF) bands, including NFC. This gives the option to select as many of the technologies required instead of being forced to select just a few ones.

#### Special features:

- Possibility to read more than 60 RFID technologies
- + Two RFID frequencies (125 kHz/13.56 MHz), NFC and BLE within ELATEC most compact and flat reader
- + Optimized design with flexible micro USB cable and optional mounting holes
- Powerful SDK for writing apps which are executed directly on the reader
- + Firmware update in the field possible
- + On-board 18 kB flash storage, e.g. for storing user accessible non-volatile data
- Supports transparent data exchange with RFID media
- CCID and PC/SC 2.01
- + Customizable inlay design



































#### TECHNICAL DATA

FREQUENCIES	125 kHz (LF) / 13.56 MHz (HF) / 2.4 GHz (BLE)		
ANTENNAS	Integrated		
HOUSING	Material: ABS+PC blend, UL94-V0. Two 3.20 mm (0.13 inch) mounting holes for OEM		
	integration (requires special inlay)		
	Color: black		
DIMENSIONS (L X W X H)	Approx. 65.50 x 45.50 x 4.00 mm / 2.58 x 1.79 x 0.16 inch		
POWER	Micro USB: 4.3 V – 5.5 V		
	PS2 classified power source according to IEC 62368-1, short-circuit current < 8 A		
CURRENT CONSUMPTION	RF field on: 135 mA typically (preliminary) / Idle: 70 mA		
TEMPERATURE RANGE	Operating: -20 °C up to +60 °C (-4 °F up to +140 °F)		
TEMPERATURE RANGE	Storage: -30 °C up to +70 °C (-22 °F up to +158 °F)		
RELATIVE HUMIDITY	5% to 95% non-condensing		
READ/WRITE DISTANCE	LF and HF: up to 80 mm / 3.15 inch, depending on environment and transponder		
	BLE: up to several meters/feet		
OPERATING MODES (USB)	USB keyboard emulation – USB virtual COM port – CCID / PC/SC 2.01		
BLUETOOTH LOW ENERGY	BLE version 4.2 (upgradable)		
MTBF	500,000 hours		
WEIGHT	Approx. 18 g / 0.64 oz (without cable and holder)		
SUPPORTED OPTIONS AND	Depending on the firmware version and installed options, ELATEC readers and modules		
	can support a wide range of RFID technologies. Please refer to the relevant ELATEC		
TRANSPONDERS	transponder matrix (available at <a href="www.elatec-rfid.com/int/transponder-technology">www.elatec-rfid.com/int/transponder-technology</a> ) for more		
	information about the available options and RFID technologies supported by the product.		
OS SUPPORT	Windows 7 (32-/64-bit) and higher versions, Linux, Android <sup>1)</sup> , iOS <sup>1)</sup> , MAC OS X <sup>1)</sup>		
PERIPHERAL INTERFACES	1 SAM slot for ID-000 card format, female micro USB, flexible cable, use only with CAB-		
	BS1 – CAB-BS7 shielded cables		
TRANSMISSION SPEED	Host: USB full speed (12 Mbit/s), HF Air: up to 848 kbit/s, BLE Air: up to 100 kbit/s		
CERTIFICATION NAME	TWN4 Slim		
CERTIFICATIONS	Non-exhaustive list <sup>2)</sup> :		
	CE/RED, FCC, IC, REACH and RoHS-III compliant		
	Standalone reader, without cable		
	T4QC-FC3B7 Standard reader		
	T4QC-FC3B7-P Reader with P option		
	T4QC-FC3B7-PI Reader with PI options		
ORDER CODES	TMNIA OF A LY		
	TWN4 Slim kits		
	Individual kits are available on request. Kits are a compilation of the TWN4 Slim reader,		
	accessories and packaging configuration (boxed or bulk packaging). After the configuration		
1)On required	of a TWN4 Slim kit, customers receive their own article number.		

¹)On request


<sup>&</sup>lt;sup>2)</sup>The product has been certified for use in many countries and regions. Contact your Sales representative for detailed information about all certifications and approvals granted to the product.



### **ACCESSORIES**

CABLES	ELATEC RFID readers and modules can be delivered with additional cables. Refer to the		
	data sheet Cables for ELATEC devices for detailed information.		
ADDITIONAL COMPONENTS	HFQC-B	TWN4 Slim mounting frame, black	
	MECH-CCK3	Cable clip kit, adhesive, black (3pcs)	
	MECH-QHC1B	TWN4 Slim HIP1 cover	
	MECH-QHC2B	TWN4 Slim HIP2 cover	
	MECH-QRBF1	TWN4 Slim rubber feet, 4pcs/set	





\_\_\_\_**.**\_\_\_

**ELATEC GmbH** 

Zeppelinstr. 1 82178 Puchheim Germany

P +49 89 552 9961 0 F +49 89 552 9961 129

E-Mail: info-rfid@elatec.com Website: elatec.com **ELATEC Systems GmbH** 

Schwieberdinger Str. 44 71636 Ludwigsburg Germany P +49 7141 309736 0

E-Mail: info-rfid@elatec.com Website: elatec.com ELATEC Inc.

1995 SW Martin Hwy Palm City • FL 34990 USA

P +1 772 210 2263 F +1 772 382 3749

E-Mail: americas-info@elatec.com Website: elatec.com ELATEC Technology (Shenzhen) LLC

918, Main Building, Tian An Cyber Times
Tower, No. 6, Tairan Fourth Road, Tian 'an
Community, Shatou Neighborhood
Futian District • Shenzhen • China
P/F +86 755 2394 6014
E-Mail: apac-info@elatec.com
Website: elatec.com

ELATEC reserves the right to change any information or data in this document without prior notice. ELATEC declines all responsibility for the use of this product with any other specification but the one mentioned above. Any additional requirement for a specific customer application has to be validated by the customer himself at his own responsibility. Where application information is given, it is only advisory and does not form part of the specification. Disclaimer: All names used in this document are registered trademarks of their respective owners.